

BIRLA INSTITUTE OF TECHNOLOGY, MESRA, RANCHI  
(MID SEMESTER EXAMINATION MO/2024)

CLASS: BTECH  
BRANCH: ECE

SEMESTER : V  
SESSION : MO/2024

SUBJECT: EC305 SIGNAL PROCESSING TECHNIQUES  
TIME: 02 Hours

FULL MARKS: 25

**INSTRUCTIONS:**

1. The question paper contains 5 questions each of 5 marks and total 25 marks.
  2. Attempt all questions.
  3. The missing data, if any, may be assumed suitably.
  4. Tables/Data handbook/Graph paper etc., if applicable, will be supplied to the candidates
- 

- |   |     |           |           |
|---|-----|-----------|-----------|
| Q.1(a) Sketch the pole-zero plot of the system $H(z) = \frac{z^2+0.25}{(z-0.5)(z^2+3z+2.5)}$ and comment on its stability.  | [2] | CO<br>CO2 | BL<br>BL3 |
| Q.1(b) Describe the minimum phase and maximum phase DSP system with example.  | [3] | CO1       | BL1       |
| Q.2(a) Compare Z-transform with Fourier transform.  | [2] | CO2       | BL2       |
| Q.2(b) Using partial fraction expansion, find the inverse Z-transform of the signal<br>$X(z) = \frac{1}{1+3z^{-1}+2z^{-2}}$ ROC: $ z  > 2$                                  | [3] | CO1       | BL1       |
| Q.3(a) Compute the periodic convolution of the sequence $x_1(n) = \{1,2,2,1\}$ and $x_2(n) = \{2,1,1,2\}$   | [2] | CO1       | BL3       |
| Q.3(b) Find the 4-point DFT of the sequence $x(n) = \{1,2,3,4\}$ using decimation in time FFT method.   | [3] | CO1       | BL1       |
| Q.4(a) Obtain the direct form-II structure of the discrete time system defined as<br>$y(n) = -0.2y(n-1) + 0.6y(n-2) + 0.4x(n) - 0.12x(n-2)$                                 | [2] | CO2       | BL3       |
| Q.4(b) Realize the cascade structure of the discrete time causal system<br>$H(z) = \frac{0.5(1-z^{-2})}{1+1.3z^{-1}+0.36z^{-2}}$  | [3] | CO2       | BL3       |
| Q.5(a) Explain the effect of truncation and rounding quantization in DSP system design.   | [2] | CO2       | BL2       |
| Q.5(b) Compare the explicit and implicit floating-point representation. Represent the real number 37.625 in 12-bit floating point representation in implicit normalization. | [3] | CO2       | BL2       |

:20/09/2024:M