

**BIRLA INSTITUTE OF TECHNOLOGY, MESRA, RANCHI
(MID SEMESTER EXAMINATION MO/2024)**

**CLASS: BTECH
BRANCH: EEE**

**SEMESTER : VII
SESSION : MO/2024**

SUBJECT: EE437 INDUSTRIAL DRIVES AND CONTROL

TIME: 02 Hours

FULL MARKS: 25

INSTRUCTIONS:

1. The question paper contains 5 questions each of 5 marks and total 25 marks.
2. Attempt all questions.
3. The missing data, if any, may be assumed suitably.
4. Tables/Data handbook/Graph paper etc., if applicable, will be supplied to the candidates

		CO	BL
Q.1(a) Draw the block diagram of an electrical drive. Explain each function of the drive block system	[2]	1	2
Q.1(b) Classify different types of load torques. Interpret the nature of each load torque	[3]	1	2
Q.2(a) Derive the expression for moment of inertia and load torque of a system of loads with translational motion interconnected with motor-load system in rotational motion. Moment of inertia of motor coupled with rotational motion load be J_0 , load torque directly coupled to the motor be T_{l0} , mass, velocity and force of load under translational motion be M_1 kg, V_1 m/s, and F_1 N.	[2]	2	3
Q.2(b) A motor has two loads. One has rotational motion. It is coupled to the motor through a reduction gear with $a = 0.1$ and efficiency of 90%. The load has moment of inertia of $10\text{Kg}m^2$ and a torque of 10 Nm. Other load has translational motion and consists of 1000Kg weight to lifted up to a uniform speed of 1.5m/s. Coupling between this load and the motor has efficiency of 85%. Motor has an inertia of $0.2\text{kg}m^2$. And runs at a constant speed of 1420 rpm. Determine equivalent inertia referred to the motor shaft and torque developed by the motor.	[3]	2	3
Q.3(a) Obtain the thermal model of a motor for temperature rise of the system	[2]	2	3
Q.3(b) A motor operates on a periodic duty cycle in which it is clutched to its load for 10 min and declutched to run on no-load for 20 min. minimum temperature rise is 40°C . Heating and cooling time constants are equal and have a value of 60 min. When the load is declutched continuously the temperature rise is 15°C . Determine i) maximum temperature during the duty cycle, and ii) temperature when the load is clutched continuously.	[3]	2	3
Q.4(a) A constant speed drive has the following duty cycle; (i)Load rising from 0 to 400kW : 5 min (ii)Uniform load of 500kW : 5 min. (iii) Regenerative power of 400kW returned to the supply : 4 min (iv) Remains idle for : 2 min Estimate the power rating of the motor. Assume the losses to be proportional to $(\text{power})^2$	[2]	2	3
Q.4(b) Classify different classes of motor duty with a suitable diagram of each motor duty	[3]	2	3
Q.5(a) Analyze the performance characteristic of the DC motor using speed-torque characteristics and torque-armature current characteristics	[2]	3	
Q.5(b) A 200 V, 10.5 A, 2000 rpm shunt motor has the armature and field resistance of 0.5 and 400 Ω respectively. It drives a load whose torque is constant at rated motor torque. Calculation motor speed if source voltage drops to 175 V.	[3]	3	4

:18/09/2024:M